



Product Data Sheet

ATS1190

ATS Smart Card Reader

Product Overview

The ATS1190 smart card readers connect directly on the RS485 data bus of the control panel or 4-Door Controller and may be configured and addressed via a LCD keypad. Some security options (Site code & 4-byte security code) are only programmable via TITAN and configuration cards. The ATS1190 is supplied standard with a white removable dress cover, which can be interchanged with one of four other colours available (see Ordering Information).

High quality cards & key fobs

Both the smart chip and antenna are embedded inside the cards & fobs. Printing is possible on the cards using any industry standard printer. The ATS1472 cards feature a programmable magnetic stripe for Time & Attendance or other applications.

Security Features

The ATS smart card technology has the ability to program a unique 268 million, 4-byte, combination security code (values from 0 through 127 are applicable for EMEA). This allows the memory card to unlock/open/disarm based on three keys; the card number, the Site code and the 4-byte security code. Once a 4-byte security code has been created, downloaded to the programmer and the cards, it is not possible to read the memory on the card or even recognise the card memory at any other reader or TITAN and programmer combination. Communications between TITAN and the programmer may also be password protected to prevent the 4-byte security code from being uploaded from the programmer into another PC running TITAN.



Standard Features

- Full epoxy filled weather proof construction
- Standard white snap-on cover (optional red, black, beige, grey)

ATS1190

ATS Smart Card Reader

Specifications

Supply voltage	9 - 14 V
Current consumption	25 - 80 mA
Open collector output	1(25 mA max)
"Request to exit" input	Yes
Max. distance from panel	1.5 km
Max. number per panel bus	16
Specified cable	Aritech WCAT 52/54 or equivalent
Data bus monitoring	Continuously monitored for offline condition of all devices on data bus
Addressing	Via keypad, TITAN or config. card
IP rating	IP54
Dimensions (W x H x D)	36 x 110 x 20 mm
Operating temperature	-35 to +66°C
Colour	5 colours
Programmable OC output	pulse from 1 msec to 2.5 secs time from 1 sec to 193 days latch
Connectivity	RS485 data bus device or standard Wiegand for connection on the 4 reader inputs of the ATS1250
Read range (cm)	6 - 8
Optical pry-off tamper sensor	Yes
Epoxy-filled weatherproof construction	Yes
Red & Blue LEDs	Configurable as nightlight, lock status or alarm area status supplied with 2.5 m of cable

Ordering Information

Part No.	Description
ATS1190	ATS Smart Card Reader
ATS1660	ATS1190 snap-on cover, white (10 pieces)
ATS1661	ATS1190 snap-on cover, red (10 pieces)
ATS1662	ATS1190 snap-on cover, grey (10 pieces)
ATS1663	ATS1190 snap-on cover, beige (10 pieces)
ATS1664	ATS1190 snap-on cover, black (10 pieces)
ATS1471	ATS Keyfob
ATS1475	ATS proximity card packed by 10 pcs.
ATS1476	ATS proximity card, with Magstripe packed by 10 pcs.
ATS1477	ATS fibertag, packed by 10.

Read/Write Encryption

The ATS Smart card technology also features an exclusive read/write encryption. When a card is presented at a reader, data are downloaded into the reader, encrypted and re-written back into the card. The readers can also be configured to operate in stand-alone or connected to control devices like office equipment or vending machines. This function enables credits to be assigned on user cards and deducted by the readers, purely on a usage basis. Up to 65535 credits may be allocated in up to 4 different banks with 16 access levels and 4 locations. The reader determines of which bank credits have to be deducted and the number of credits per valid presentation.

Multiple Card Badging

The ATS1190 smart card reader can be used for arming/disarming areas as well as for access applications. It is suitable for using the multiple card badging techniques which are available for the advisor MASTER control panel family. A user could arm the system in the evenings by badging his card three times within 10 seconds interval. Another application could be for doors which can be programmed so that badging once unlocks, badging twice with the same card keeps the door unlocked to allow people in and out without card, and badging three times re-locks the door.

